

inLOOP HOME INSTALLATION

STEP 1 - Install the wire

included with inLOOP HOME above the ceiling, around the room or under the floor. The wire must form a continuous loop around the listening area. Do not install the loop wire close to and parallel with audio lines, telephone or video cables.

Do not install the wire more than 9' above the floor.

SECURE THE WIRE SAFELY. MAKE SURE IT IS NOT A

TRIP HAZARD **CONSIDER AN OPTIONAL PERSONAL inLOOP PAD FOR EASIER INSTALLATION.**



STEP 2 - Connect the wire. Strip 1/2" of plastic from the ends of the loop wire. Loosen the red and black "LOOP WIRE" connectors. Insert one end of the bare wire into the opening in the black terminal and tighten the connector to secure the wire. Insert the other end of the wire into the opening in the red terminal and tighten the connector to secure the wire.



STEP 3 - Connect the sound source

THIS PHOTO IS FOR ILLUSTRATION PURPOSES ONLY. YOUR DEVICE WILL LOOK DIFFERENT.



If there is a **DIGITAL COAXIAL (COAX)** or **OPTICAL OUT**, the optional **DIGITAL inLOOP CONNECTOR** (sold separately) will connect digital outputs to inLOOP HOME.



There are a number of different types of audio outputs. Your connection depends on the model and type of TV, stereo or cable box. If your system has a left (L) and right (R) AUDIO OUT like the photo to the left, install the included cable from this output to the "ANALOG INPUT" on inLOOP HOME, like the two photos below.



If there are no audio outputs, or you do not wish to purchase the Digital inLOOP Connector, the sound can be picked up from a speaker by the built in microphone in the back left corner of inLOOP HOME. It is as simple as positioning inLOOP HOME in front of the speaker and depressing the **MIC/LINE** button.

STEP 4 - Adjust the volume. Plug the power adapter into the wall and inLOOP HOME. Move the power switch to the on position. Turn the VOLUME knob until the LOOP ACTIVITY light flickers. Adjust the TONE as needed.



info@inLOOP.tv

inLOOP

569 South State Street

Shelby, MI 49455

(231) 798- 2399